



Harmonic Filter Reactors (Basic / Standard)

Guide to selection: Harmonic Filter Reactors → Capacitors

// Guide to selection: Harmonic Filter Reactors → Capacitors

Basic Harmonic Filter Reactors

Detuning factor $p = 7\%$

Article-No.	Type	Q [kvar]	C [μF]	Type and quantity of the capacitors required									
				LKT 10-525-DP Article-No. 31-10517	LKT 11,7-400-DL Article-No. 31-10604	LKT 28,2-440-DP Article-No. 31-10535							

FDK: $V_N = 400\text{ V} / 50\text{ Hz}$

88-02102	FDK 6,25-400-P7	6.3	3 x 38.5	1														
88-02044	FDK 12,5-400-P7	12.5	3 x 77.6		1													
88-02042	FDK 25-400-P7	25.0	3 x 155.2		2	1												
88-02043	FDK 50-400-P7	50.0	3 x 310.4		4	2												
88-02083	FDK 75-400-P7	75.0	3 x 465.6		6	3												
88-02084	FDK 100-400-P7	100.0	3 x 620.8		8	4												

Article-No.	Type	Q	C	Type and quantity of the capacitors required										
				LKT 15,5-480-DP Article-No. 31-10382										
		[kvar]	[μ F]											

FDK: $V_N = 415 \text{ V} / 50 \text{ Hz}$

88-02088	FDK 12,5-415-P7	12.5	3 x 71.4	1										
88-02089	FDK 25-415-P7	25.0	3 x 142.8	2										
88-02090	FDK 50-415-P7	50.0	3 x 285.6	4										
88-02091	FDK 75-415-P7	75.0	3 x 428.4	6										
88-02191	FDK 100-415-P7	100.0	3 x 572.3	8										

Article-No.	Type	Q	C	Type and quantity of the capacitors required										
				LKT 20-690-DP Article-No. 31-10564										
		[kvar]	[μ F]											

FDK: $V_N = 525 \text{ V} / 50 \text{ Hz}$

88-02066	FDK 12,5-525-P7	12.5	3 x 44.7	1										
88-02067	FDK 25-525-P7	25.0	3 x 89.4	2										
88-02068	FDK 50-525-P7	50.0	3 x 178.8	4										
88-02069	FDK 75-525-P7	75.0	3 x 268.2	6										
88-02070	FDK 100-525-P7	100.0	3 x 357.6	8										
88-02071	FDK 150-525-P7	150.0	3 x 536.4	12										
88-02072	FDK 200-525-P7	200.0	3 x 715.2	16										

Article-No.	Type	Q	C	Type and quantity of the capacitors required										
				LKT 10-625-DP Article-No. 31-10517	LKT 11,7-400-DL Article-No. 31-10604	LKT 28,2-440-DP Article-No. 31-10535								
		[kvar]	[μ F]											

FDKT: $V_N = 400 \text{ V} / 50 \text{ Hz}$

88-02103	FDKT 6,25-400-P7	6.3	3 x 38.5	1										
88-02045	FDKT 12,5-400-P7	12.5	3 x 77.6		1									
88-02046	FDKT 25-400-P7	25.0	3 x 155.2		2	1								
88-02047	FDKT 50-400-P7	50.0	3 x 310.4		4	2								
88-02093	FDKT 75-400-P7	75.0	3 x 465.6		6	3								
88-02094	FDKT 100-400-P7	100.0	3 x 620.8		8	4								

Technical Annex

Guide to selection: Harmonic Filter Reactors → Capacitors

Article-No.	Type	Q	C	LKT 15,5-480-DP Article-No. 31-10382	Type and quantity of the capacitors required									

FDKT: $V_N = 415 \text{ V} / 50 \text{ Hz}$

88-02098	FDKT 12,5-415-P7	12.5	3 x 71.4	1																
88-02099	FDKT 25-415-P7	25.0	3 x 142.8	2																
88-02100	FDKT 50-415-P7	50.0	3 x 285.6	4																
88-02101	FDKT 75-415-P7	75.0	3 x 428.4	6																
88-02190	FDKT 100-415-P7	100.0	3 x 572.3	8																

Article-No.	Type	Q	C	LKT 20-690-DP Article-No. 31-10564	Type and quantity of the capacitors required									

FDK: $V_N = 525 \text{ V} / 50 \text{ Hz}$

88-02146	FDKT 12,5-525-P7	12.5	3 x 44.7	1																
88-02147	FDKT 25-525-P7	25.0	3 x 89.4	2																
88-02148	FDKT 50-525-P7	50.0	3 x 178.8	4																
88-02149	FDKT 75-525-P7	75.0	3 x 268.2	6																
88-02150	FDKT 100-525-P7	100.0	3 x 357.6	8																
88-02151	FDKT 150-525-P7	150.0	3 x 536.4	12																
88-02152	FDKT 200-525-P7	200.0	3 x 715.2	16																

Detuning factor $p = 14 \%$

Article-No.	Type	Q	C	LKT 15,5-480-DP Article-No. 31-10382	Type and quantity of the capacitors required									

FDK: $V_N = 400 \text{ V} / 50 \text{ Hz}$

88-02085	FDK 12,5-400-P1	12.5	3 x 71.4	1																
88-02086	FDK 25-400-P1	25.0	3 x 142.8	2																
88-02087	FDK 50-400-P1	50.0	3 x 285.6	4																

Article-No.	Type	Q	C	Type and quantity of the capacitors required									
				[kvar]	[μ F]								

FDK: $V_N = 525$ V / 50 Hz

88-02073	FDK 12,5-525-P1	12.5	3 x 41.1																	
88-02074	FDK 25-525-P1	25.0	3 x 82.2																	
88-02075	FDK 50-525-P1	50.0	3 x 164.4																	
88-02076	FDK 75-525-P1	75.0	3 x 246.6	Type and quantity of the capacitors required on request																
88-02077	FDK 100-525-P1	100.0	3 x 328.8																	
88-02078	FDK 150-525-P1	150.0	3 x 439.2																	
88-02079	FDK 200-525-P1	200.0	3 x 657.6																	

Article-No.	Type	Q	C	LKT 15,5-480-DP Article-No. 31-10382	Type and quantity of the capacitors required									
					[kvar]	[μ F]								

FDK: $V_N = 400$ V / 50 Hz

88-02095	FDKT 12,5-400-P1	12.5	3 x 71.4	1																
88-02096	FDKT 25-400-P1	25.0	3 x 142.8	2																
88-02097	FDKT 50-400-P1	50.0	3 x 285.6	4																

Article-No.	Type	Q	C	Type and quantity of the capacitors required									
				[kvar]	[μ F]								

FDK: $V_N = 525$ V / 50 Hz

88-02153	FDKT 12,5-525-P1	12.5	3 x 41.1																	
88-02154	FDKT 25-525-P1	25.0	3 x 82.2																	
88-02155	FDKT 50-525-P1	50.0	3 x 164.4																	
88-02156	FDKT 75-525-P1	75.0	3 x 246.6	Type and quantity of the capacitors required on request																
88-02157	FDKT 100-525-P1	100.0	3 x 328.8																	
88-02158	FDKT 150-525-P1	150.0	3 x 439.2																	
88-02159	FDKT 200-525-P1	200.0	3 x 657.6																	

Technical Annex

Guide to selection: Harmonic Filter Reactors → Capacitors

Standard Harmonic Filter Reactors

Detuning factor $p = 5.67\%$

Article-No.	Type	Q [kvar]	C [μF]	Type and quantity of the capacitors required									
				LKT 11,7-400-DL Article-No. 31-10604	LKT 28,2-440-DP Article-No. 31-10535								

FDK: $V_N = 400\text{ V} / 50\text{ Hz}$

88-02141	FDR 25-400-P5	25.0	3 x 155.2	2	1															
88-02142	FDR 50-400-P5	50.0	3 x 310.4	4	2															

Detuning factor $p = 7\%$

Article-No.	Type	Q [kvar]	C [μF]	Type and quantity of the capacitors required									
				LKT 10-440-DP Article-No. 31-10508	LKT 10-525-DP Article-No. 31-10517	LKT 10-400-DP Article-No. 31-10380	LKT 12,5-400-DP Article-No. 31-10502						

FDK: $V_N = 230\text{ V} / 50\text{ Hz}$

88-01980	FDR 5-230-P7	5.0	3 x 93.3	1	1															
88-01575	FKD 10-230-P7	10.0	3 x 200.0			3														
88-01974	FDR 12,5-230-P7	12.5	3 x 232.1			1	2													
88-01583	FKD 16,7-230-P7	16.7	3 x 334.0				4													
88-01576	FKD 20-230-P7	20.0	3 x 400.0			6														
88-01943	FDR 25-230-P7	25.0	3 x 464.2			2	4													
88-01568	FKD 33-230-P7	33.0	3 x 668.0				8													

Article-No.	Type	Q	C	Type and quantity of the capacitors required												
				LKT 3,6-480-DL Article-No. 31-10613	LKT 4,5-480-DL Article-No. 31-10614	LKT 6,25-400-DL Article-No. 31-10601	LKT 9,1-440-DL Article-No. 31-10609	LKT 12,1-440-DL Article-No. 31-10610	LKT 11,7-400-DL Article-No. 31-10604	LKT 12,5-400-DL Article-No. 31-10386	LKT 28,2-440-DP Article-No. 31-10535	LKT 10-440-DP Article-No. 31-10508	LKT 10,4-480-DL Article-No. 31-10617	LKT 15,5-480-DP Article-No. 31-10382		

FDK: $V_N = 400 \text{ V} / 50 \text{ Hz}$

88-01640	FKD 2,5-400-P7	2.5	3 x 16.6	1																
88-01719	FKD 3,13-400-P7	3.13	3 x 19.9		1															
88-01481	FKD 5-400-P7	5.0	3 x 33.2																	
88-01410	FKD 6,25-400-P7	6.25	3 x 41.5			1														
88-01482	FKD 7,5-400-P7	7.5	3 x 49.7				1													
88-01479	FKD 10-400-P7	10.0	3 x 66.3					1												
88-01767	FDR 12,5-400-P7	12.5	3 x 77.1						1											
88-01362	FKD 15-400-P7	15.0	3 x 99.5				2													
88-01922	FDR 16,7-400-P7	16.7	3 x 102.9										1	1						
88-01363	FKD 20-400-P7	20.0	3 x 132.6					2												
88-01768	FDR 25-400-P7	25.0	3 x 154.2						2	or	1									
88-01484	FKD 30-400-P7	30.0	3 x 198.9					3												
88-01923	FDR 33,3-400-P7	33.3	3 x 205.8										2	2						
88-02053	FDR 37,5-400-P7	37.5	3 x 213.9																3	
88-01782	FDR 40-400-P7	40.0	3 x 248.8							3										
88-01769	FDR 50-400-P7	50.0	3 x 308.4						4	or	2									

Article-No.	Type	Q	C	Type and quantity of the capacitors required												
				LKT 7,8-480-DL Article-No. 31-10616												

FDK: $V_N = 415 \text{ V} / 50 \text{ Hz}$

88-02034	FDR 6,25-415-P7	6.3	3 x 35.9	1																
88-01937	FDR 12,5-415-P7	12.5	3 x 71.4	2																
88-01938	FDR 25-415-P7	25.0	3 x 142.8	4																
88-01930	FDR 50-415-P7	50.0	3 x 285.6	8																

Technical Annex

Guide to selection: Harmonic Filter Reactors → Capacitors

Article-No.	Type	Q	C	Type and quantity of the capacitors required																
				LKT 8,33-525-DL Article-No. 31-10622																
		[kvar]	[µF]																	

FDK: $V_N = 440 \text{ V} / 50 \text{ Hz}$

88-02160	FDR 6,25-440-P7	6.3	3 x 32.1	1																
88-02161	FDR 12,5-440-P7	12.5	3 x 64.2	2																
88-01008	FKD 25-440-P7	25.0	3 x 132.8	4																
88-01124	FKD 50-440-P7	50.0	3 x 265.6	8																

Article-No.	Type	Q	C	Type and quantity of the capacitors required																
				LKT 4,17-525-DL Article-No. 31-10619	LKT 5,9-525-DL Article-No. 31-10620	LKT 7,7-525-DL Article-No. 31-10621														
		[kvar]	[µF]																	

FDK: $V_N = 525 \text{ V} / 50 \text{ Hz}$

88-01801	FDR 6,25-525-P7	6.3	3 x 22.9		1															
88-01802	FDR 12,5-525-P7	12.5	3 x 45.8		2															
88-01080	FKD 20-525-P7	20.0	3 x 80.5	1		2														
88-01838	FDR 25-525-P7	25.0	3 x 89.5			3														
88-01837	FDR 50-525-P7	50.0	3 x 179.0			6														
88-01872	FDR 50-525-P7	50.0	3 x 179.0			6														

Article-No.	Type	Q	C	Type and quantity of the capacitors required																
				LKT 13,3-800-DP Article-No. 31-10572	LKT 28,2-760-DP Article-No. 31-10569															
		[kvar]	[µF]																	

FDK: $V_N = 690 \text{ V} / 50 \text{ Hz}$

88-01825	FKD 10-690-P7	10.0	3 x 22.1	1																
88-01932	FDR 25-690-P7	25.0	3 x 51.5		2															
88-01933	FDR 50-690-P7	50.0	3 x 103.1		4															

Article-No.	Type	Q	C	Type and quantity of the capacitors required																
				LKT 10-525-DP Article-No. 31-10517	LKT 11,7-400-DL Article-No. 31-10604	LKT 10-400-DP Article-No. 31-10380	LKT 12,5-400-DP Article-No. 31-10502													
		[kvar]	[μF]																	

FDK: $V_N = 230 \text{ V} / 60 \text{ Hz}$

88-01996	FDR 2,5-230-P7-60	2.5	3 x 38.5	1																
88-01997	FDR 5-230-P7-60	5.0	3 x 77.3		1															
88-01998	FDR 10-230-P7-60	10.0	3 x 154.6		2															
88-02140	FDR 12,5-230-P7-60	12.5	3 x 194.3																	
88-02001	FDR 20-230-P7-60	20.0	3 x 309.2		4															
88-01892	FDR 25-230-P7-60	25.0	3 x 385.5				2	3												

Article-No.	Type	Q	C	Type and quantity of the capacitors required																
				LKT 15,5-480-DP Article-No. 31-10513																
		[kvar]	[μF]																	

FDK: $V_N = 380 \text{ V} / 60 \text{ Hz}$

88-02179	FDR 12,5-380-P7-60	12.5	3 x 71.4	1																
88-02180	FDR 25-380-P7-60	25.0	3 x 142.8	2																
88-02181	FDR 50-380-P7-60	50.0	3 x 285.6	4																

Article-No.	Type	Q	C	Type and quantity of the capacitors required																
				LKT 8,33-525-DL Article-No. 31-10622																
		[kvar]	[μF]																	

FDK: $V_N = 400 \text{ V} / 60 \text{ Hz}$

88-01963	FDR 12,5-400-P7-60	12.5	3 x 64.2	2																
88-01964	FDR 25-400-P7-60	25.0	3 x 128.1	4																
88-01965	FDR 50-400-P7-60	50.0	3 x 256.9	8																

Article-No.	Type	Q [kvar]	C [μF]	Type and quantity of the capacitors required									
				LKT 7,7-525-DL Article-No. 31-10621	LKT 8,33-525-DL Article-No. 31-10622	LKT 5,9-525-DL Article-No. 31-10620	LKT 15,5-480-DP Article-No. 31-10382	LKT 7,8-480-DL Article-No. 31-10616					

FDK: V_N = 440 V / 60 Hz

88-01914	FKD 6,25-440-P7-60	6.3	3 x 29.9	1																
88-01795	FDR 7,5-440-P7-60	7.5	3 x 32.0		1															
88-01883	FDR 12,5-440-P7-60	12.5	3 x 54.8		1	1														
88-01796	FDR 15-440-P7-60	15.0	3 x 64.0		2															
88-01884	FDR 25-440-P7-60	25.0	3 x 107.2					1	1											
88-01797	FDR 30-440-P7-60	30.0	3 x 128.0		4															
88-01875	FDR 50-440-P7-60	50.0	3 x 214.2					3												

Article-No.	Type	Q [kvar]	C [μF]	Type and quantity of the capacitors required									
				LKT 5-690-DP Article-No. 31-10560	LKT 4,5-480-DL Article-No. 31-10614	LKT 10-525-DP Article-No. 31-10517	LKT 12,5-525-DP Article-No. 31-10516						

FDK: V_N = 460 V / 60 Hz

88-02123	FKD 2,5-460-P7-60	2.5	3 x 11.1	1																
88-02124	FKD 5-460-P7-60	5.0	3 x 20.7		1															
88-02125	FDR 10-460-P7-60	10.0	3 x 38.5			1														
88-01854	FDR 12,5-460-P7-60	12.5	3 x 48.1					1												
88-01855	FDR 25-460-P7-60	25.0	3 x 96.2					2												
88-01856	FDR 50-460-P7-60	50.0	3 x 192.4					4												

Article-No.	Type	Q [kvar]	C [μF]	Type and quantity of the capacitors required									
				LKT 5,9-525-DL Article-No. 31-10620	LKT 7,7-525-DL Article-No. 31-10621	LKT 8,33-525-DL Article-No. 31-10622							

FDK: V_N = 480 V / 60 Hz

88-01962	FDR 12,5-480-P7-60	12.5	3 x 45.6	2																
88-02056	FDR 25-480-P7-60	25.0	3 x 89.7		3															
88-01732	FKD 50-480-P7-60	50.0	3 x 192.0					6												

Detuning factor $p = 8\%$

Article-No.	Type	Q	C	Type and quantity of the capacitors required												
				LKT 3,6-480-DL Article-No. 31-10613	LKT 4,5-480-DL Article-No. 31-10614	LKT 6,25-400-DL Article-No. 31-10601	LKT 9,1-440-DL Article-No. 31-10609	LKT 12,1-440-DL Article-No. 31-10610	LKT 11,7-400-DL Article-No. 31-10604	LKT 12,5-400-DL Article-No. 31-10386	LKT 28,2-440-DP Article-No. 31-10535	LKT 10-440-DP Article-No. 31-10508	LKT 10,4-480-DL Article-No. 31-10617	LKT 15,5-480-DP Article-No. 331-10382		

FDK: $V_N = 400\text{ V} / 50\text{ Hz}$

88-01678	FKD 2,5-400-P8	2.5	3 x 16.6	1															
88-01941	FKD 3,13-400-P8	3.1	3 x 19.9		1														
88-01518	FKD 5-400-P8	5.0	3 x 33.2																
88-01492	FKD 6,25-400-P8	6.3	3 x 41.5			1													
88-01519	FKD 7,5-400-P8	7.5	3 x 49.7				1												
88-01520	FKD 10-400-P8	10.0	3 x 66.3					1											
88-01770	FDR 12,5-400-P8	12.5	3 x 77.1						1										
88-01381	FKD 15-400-P8	15.0	3 x 99.5				2												
88-01926	FDR 16,7-400-P8	16.7	3 x 102.9										1	1					
88-01382	FKD 20-400-P8	20.0	3 x 132.6					2											
88-01771	FDR 25-400-P8	25.0	3 x 154.2						2	or	1								
88-01387	FKD 30-400-P8	30.0	3 x 198.9					3											
88-01927	FDR 33,3-400-P8	33.3	3 x 205.9										2	2					
88-02054	FDR 37,5-400-P8	37.5	3 x 231.9															3	
88-01781	FDR 40-400-P8	40.0	3 x 248.8							3									
88-01772	FDR 50-400-P8	50.0	3 x 308.4						4	or	2								

Article-No.	Type	Q	C	Type and quantity of the capacitors required												
				LKT 7,8-480-DL Article-No. 31-10616												

FDK: $V_N = 480\text{ V} / 50\text{ Hz}$

88-01985	FDR 25-480-P8	25.0	3 x 107.4	3															
88-01986	FDR 50-480-P8	50.0	3 x 214.8	6															

Article-No.	Type	Q	C	Type and quantity of the capacitors required																
				LKT 4,17-525-DL Article-No. 31-10619	LKT 7,7-525-DL Article-No. 31-10621	LKT 8,33-525-DL Article-No. 31-10622														
		[kvar]	[μF]																	

FDK: $V_N = 525 \text{ V} / 50 \text{ Hz}$

88-01845	FKD 20-525-P8	20.0	3 x 80.5	1	2															
88-01840	FDR 25-525-P8	25.0	3 x 89.5		3															
88-01846	FDR 30-525-P8	30.0	3 x 112.7	1		3														
88-01839	FDR 50-525-P8	50.0	3 x 179.0		6															
88-01871	FDR 50-525-P8	50.0	3 x 179.0		6															

Article-No.	Type	Q	C	Type and quantity of the capacitors required																
				LKT 28,2-760-DP Article-No. 31-10569	LKT 6,7-800-DP Article-No. 31-10570	LKT 26,7-800-DP Article-No. 31-10574														
		[kvar]	[μF]																	

FDK: $V_N = 690 \text{ V} / 50 \text{ Hz}$

88-01807	FKD 25-690-P8	25.0	3 x 55.3		1	2														
88-01912	FDR 50-690-P8	50.0	3 x 103.1	4																

Detuning factor $p = 14\%$

Article-No.	Type	Q [kvar]	C [μ F]	Type and quantity of the capacitors required									
				LKT 10-400-DP Article-No. 31-10380	LKT 9,3-400-DL Article-No. 31-10602	LKT 12,5-400-DP Article-No. 31-10502							

FDK: $V_N = 230\text{ V} / 50\text{ Hz}$

88-02020	FDR 15-230-P1	15.0	3 x 260.3	3	1															
88-01868	FDR 30-230-P1	30.0	3 x 519.9	4		3														

Article-No.	Type	Q [kvar]	C [μ F]	Type and quantity of the capacitors required													
				LKT 3,6-480-DL Article-No. 31-10613	LKT 7,8-480-DL Article-No. 31-10616	LKT 5,9-525-DL Article-No. 31-10620	LKT 4,5-480-DL Article-No. 31-10388	LKT 7,7-525-DL Article-No. 31-10621	LKT 15,5-480-DP Article-No. 31-10382	LKT 7,6-440-DL Article-No. 31-10608	LKT 10,4-480-DL Article-No. 31-10617	LKT 12,1-440-DL Article-No. 31-10610	LKT 9,1-440-DL Article-No. 31-10387				

FDK: $V_N = 400\text{ V} / 50\text{ Hz}$

88-01834	FDR 3,13-400-P1	3.1	3 x 16.6	1																
88-02186	FDR 6,25-400-P1	6.3	3 x 35.9		1															
88-01979	FDR 7,5-400-P1	7.5	3 x 43.4			1	1													
88-01695	FDR 10-400-P1	10.0	3 x 59.8					2												
88-01168	FDR 12,5-400-P1	12.5	3 x 71.4						1											
88-02187	FDR 15-400-P1	15.0	3 x 89.6							1	1									
88-02177	FDR 16,7-400-P1	16.7	3 x 95.8									2								
88-01038	FDR 20-400-P1	20.0	3 x 113.1							1	1									
88-01171	FDR 25-400-P1	25.0	3 x 142.8							2										
88-01039	FDR 30-400-P1	30.0	3 x 174.3								1		2							
88-01925	FDR 33,3-400-P1	33.3	3 x 190.7							2		1								
88-02176	FDR 37,5-400-P1	37.5	3 x 214.2							3										
88-02175	FDR 40-400-P1	40.0	3 x 232.4											2	2					
88-02174	FDR 50-400-P1	50.0	3 x 285.6							4										

Article-No.	Type	Q	C	Type and quantity of the capacitors required																
				LKT 7,2-480-DL Article-No. 31-10615																
		[kvar]	[μF]																	

FDK: V_N = 415 V / 50 Hz

88-01956	FDR 25-415-P1	25.0	3 x 132.6	4																
88-01957	FDR 50-415-P1	50.0	3 x 265.2	8																

Article-No.	Type	Q	C	Type and quantity of the capacitors required																
				LKT 7,7-525-DL Article-No. 31-10621	LKT 12,5-525-DP Article-No. 31-10516															
		[kvar]	[μF]																	

FDK: V_N = 440 V / 50 Hz

88-02041	FDR 25-440-P1	25.0	3 x 118.0	4																
88-02007	FDR 50-440-P1	50.0	3 x 240.5		5															

Article-No.	Type	Q	C	Type and quantity of the capacitors required																
				LKT 15-690-DP Article-No. 31-10563																
		[kvar]	[μF]																	

FDK: V_N = 480 V / 50 Hz

88-02143	FDR 25-480-P1	25.0	3 x 100.2	3																
88-02144	FDR 50-480-P1	50.0	3 x 199.3	6																

Article-No.	Type	Q [kvar]	C [μF]	Type and quantity of the capacitors required									
				LKT 5,9-525-DL Article-No. 31-10620	LKT 7,7-525-DL Article-No. 31-10621	LKT 8,33-525-DL Article-No. 31-10622							

FDK: V_N = 525 V / 50 Hz

88-02039	FDR 12,5-525-P1	12.5	3 x 45.4	2											
88-01960	FDR 25-525-P1	25.0	3 x 84.4	1	1	1									
88-01900	FDR 50-525-P1	50.0	3 x 168.8	2	2	2									

Article-No.	Type	Q [kvar]	C [μF]	Type and quantity of the capacitors required									
				LKT 4,8-480-EP Article-No. 31-10515	LKT 6-480-EP Article-No. 31-10514	LKT 8,33-525-EP Article-No. 31-10385	LKT 3,6-480-EP Article-No. 31-10531						

FDK: V_N = 690 V / 50 Hz

88-02122	FDR 12,5-690-P1	12.5	3 x 22.1	3											
88-02120	FDR 20-690-P1	20.0	3 x 38.7	3			3								
88-01842	FDR 25-690-P1	25.0	3 x 50.0	3	3										
88-01843	FDR 50-690-P1	50.0	3 x 99.9			9									

* Type and quantity of the capacitors required on request